

X-VIEW

FMT 02



Switch On

Before to turn the unit on, check that there is a loaded battery in the compartment, if there is not, put it making the poles + and - to coincide. Press the "power" button for at least three seconds to turn the unit on in normal way.

Normal way

- Press "up" to go 1Mhz. If the frequency is 107.9 Mhz it will move to the frequency 87.6 Mhz. Keep press to continue throw the dial.
- Press "down" to go down 1Mhz. If the frequency is 107.9 Mhz it will move to the frequency 107.8 Mhz. Keep press to continue going down throw the dial.

Press "Power" to enter in the prestablished mode.

- The preengraved tunings are showed (P1 a P6)
- It will show the battery symbol
- It will show the touchline of FM (87.6 a 107.9 Mhz).

In predetermine mode

- Press "up" to go to the next tuning, if the actual tuning is P2 it will go to P3.
- Press "down" to go to the previous tuning, if the actual tuning is P2 it will go to P1.

Press "Power" again to enter

- It shows the Menu symbol.
- It shows all the tunings programmed.
- It shows the battery symbol.
- It shows FM frequency (87.6 -107.9 Mhz)

Programming Way

- Press "up" or "down" to move 1Mhz. If the actual channel is 107.9 and you press "up" it will move to 87.6 Mhz.
- Press "memory" to keep the actual frequency and enter to the normal mode.

In all modes (Normal/ Predetermine/ of Programming)

- If the transmitter of FM is feed by an external source (DC 5V) by the "DC in", the symbol of the battery will appear complete.
- If the transmitter is feed by a AAA battery, this will be indicated on the screen according to load of the battery.

To Turn off the transmitter of FM X-VIEW

- Keep press the "power" button for at least three seconds to turn off the FM transmitter (if it is in the Programming mode and you turn it off, the tunings would not be recorderd)

Advices for an appropriate use

Your new FM transmitter is a powerful emitter of radio's frequencies. In cities of population density can exist lot of radio's emitters with higher power than theirs product.

This does not occur in small cities or routes where you can operate without any inconvenient with your product.

To obtain a correctly operation in cities with lot of emitters, you should interact with your auto stereo to find the more appropriate station.

It can be possible that the digital stereo of your car look automatically radios, you should pass to the manual mode to find space without emission in its dial (the automatic mode will find the frequencies with higher emission instead of the fewer ones).

Once you get a frequency of radio, recorder it in the memory, to find it easily, the next time you turn your FM transmitter on. It will be convenient that you record the frequency in your auto stereo as in your FM transmitter.

It is recommended that you find at least two frequencies empty to keep an alternative frequency in case of troubles.

Be sure that you placed the transmitter as near you can from the stereo.